

# On Line UPS PlusPRO 1 1000VA/900Watt



**Kode** : PLUSPRO1-1000G(B)

**Brand** : Aplus

**Jenis** : UPS

**Harga** : Rp 2.610.000,00

Rp 3.430.000,00

PlusPro 1-1000G adalah produk dari APlus UPS System dengan rating 1000VA/900Watt yang memiliki desain tower dan juga fitur "Easy Battery Extender". Dilengkapi dengan external battery connector (Anderson connector) sehingga memungkinkan pengguna untuk mudah melakukan penambahan battery jika menginginkan backup time lebih lama.

**\*Penjualan produk ini termasuk battery**

**\*Pengiriman hanya jalur darat dan area pulau jawa**

**\*Garansi 1 Tahun**

**\*Garansi battery 1 bulan**

Penawaran Harga Spesial

 08112039555

## Features :

- High-performance true double-conversion On-Line UPS 1000VA
- External battery bank to extend backup time (Optional)
- Microprocessor control guarantees high reliability
- Low heat dissipation in long time operation
- Emergency power-off function (EPO)
- USB multiple communications
- Automatic self-testing function
- High efficiency mode (ECO mode)
- Output voltage regulation +/- 2%
- Power management software
- Output power factor 0.9
- Wide input range
- Fan speed control
- DC start







### Battery Type :

- VRLA 12V/9AH or VRLA 12V/7.2AH
- 2 pcs (VRLA 12V/9AH included)
- **Battery dimension 151 x 65 x 100 mm**

### Specification :

|   |   |
|---|---|
| <b>Model</b>  | <b>1KVA</b>   |
| <b>Power</b>  | <b>1000VA</b>   |
| <b>Input</b>  |   |
| <b>Normal Current (@230V/battery recharged fully)</b> | <b>4.3A</b>   |
| <b>Voltage Range</b>                                  | <b>100~300VAC</b>                                       |
| <b>Frequency Range</b>                                | <b>45 ~ 55Hz @ 50Hz system 54 ~ 66Hz @ 60Hz system</b>  |
| <b>Current Distortion(THDi)</b>                       | <b>&lt;5% (typical) @ 100% linear load</b>              |
| <b>Output</b>   |   |
| <b>Voltage</b>  | <b>200/208/220/230/240 ± 2%</b>                         |
| <b>Frequency (battery mode)</b>                       | <b>50/60Hz ± 0.05Hz</b>                                 |
| <b>Current Crest Ratio</b>                            | <b>3:01</b>   |
| <b>Voltage Distortion (THDv)</b>                      | <b>&lt; 1% @ linear load, &lt; 5% @ non-linear load</b> |
| <b>Output Waveform</b>                                | <b>Pure sine wave</b>                                   |
| <b>Efficiency</b>                                     |   |
| <b>Inverter Mode</b>                                  | <b>&gt; 88%</b>   |
| <b>ECO Mode</b>                                       | <b>&gt; 97%</b>   |
| <b>Battery</b>  |   |
| <b>Rated Battery Voltage</b>                          | <b>24VDC</b>  |
| <b>Battery Type</b>                                   | <b>12V/9AH</b>  |
| <b>Number of Internal Battery</b>                     | <b>2</b>  |
| <b>Backup Time (@ Full Load)</b>                      | <b>&gt; 3.5 mins</b>                                    |
| <b>Recharge Time (to 90%)</b>                         | <b>4 hours</b>  |

|                            |   |
|----------------------------|---|
| <b>Ambient Temperature</b> | 0°C ~ 40°C  |
| <b>Storage Temperature</b> | -25°C ~ 55°C                                      |
| <b>Noise Level</b>         | 40dB @1 meter                                     |
| <b>Altitude</b>            | < 1000m   |
|                            | (The load no derating)                            |
|                            | 1000m < Altitude ≤ 3000m                          |
|                            | (The load should derating 1 % for every up 100m ) |
| <b>Relative Humidity</b>   | <95%  |

### External Battery Installation :



- 24VDC Battery (Recommendation VRLA type Battery)

### Manual :

[PLUSPRO1-MANUAL](#)

*\* Harga, spesifikasi, dan ketersediaan bisa berubah dan tidak mengikat*

**URL :** <https://www.citraweb.com/produk/963/>

**Informasi lebih lanjut, pemesanan dan pembelian, hubungi: 0274-554444 atau email [sales@citraweb.com](mailto:sales@citraweb.com)**

[www.citraweb.com](http://www.citraweb.com)